

JB-EYE INTRUDER ALARM NEW KEY FOB INSTRUCTIONS

NB: THESE INSTRUCTIONS SHOW HOW TO PROGRAM A FOB INTO A SYSTEM TO SIMPLY ALLOW THE USER TO SET AND UNSET ALL DEFAULT AREAS OF THE ALARM ON PRESENTATION OF THEIR FOB. SHOULD YOU HAVE MORE COMPLEX REQUIREMENTS SUCH AS MULTIPLE AREAS THAT REQUIRE SETTING AND UNSETTING INDEPENDENTLY OR WISH TO RESTRICT USERS TO CERTAIN FUNCTIONS PLEASE REFER TO THE INSTRUCTION BOOKLET PROVIDED AT HANDOVER.

1. Start at the normal unset screen as shown below. To return to this screen press the 'NO' key twice:

```
JB-EYE      E1234
Time        09:00c
```

2. Press the 'D' button

```
Enter Your Code
                [    ]
```

3. Enter your manager code. If you don't know your manager code please call our office.

```
SET DATE & TIME?
```

4. Press the 'NO' button twice

```
CHANGE CODES?
```

5. Press the 'YES' button

```
Add New User?
```

If display is as above proceed to step 8 otherwise the display will be as below

```
Change User Codes?
```

6. Press the 'Yes' button. The display will show details of the first fob programmed

```
User Number [001]
Phillip Jones
```

7. Press the 'D' button until the display shows a User Number with a blank second line

```
User Number [005]
```

8. Press the 'YES' button

Empty [004]

The number shown will depend on how many fobs are already programmed into your system.

9. Press the 'YES' button

Enter User Code

[]

NOTE: If the display show [XXXXXX] this user number is already programmed. Press the 'No' key and then Return to step 7

10. Hold the new fob to the 'JB-EYE' logo to the left of the display screen until the system beeps once

Enter User Code

[XXXXXX]

11. Press the 'YES' button

User Type

User [0]

12. Press the 'YES' button until the display shows:

User Name

—

13. Use the numeric keys to enter the required user name. The 'D' button moves the cursor to the right. The 'B' button moves the cursor to the left. The 'C' button clears the cursor. The system has predictive text, if the name that appears is not as required use the buttons to amend accordingly.

User Name

John Smith

14. When you have the desired name press the 'YES' button

Empty [005]

If the display shows as above and you have more fobs to enter press the 'YES' button and repeat procedure from Step 9

User Number [004]

John Smith

If the display shows as above and you have more fobs to enter press the 'YES' button and repeat procedure from step 7

15. If you have finished press the 'NO' button until the display shows:



EXIT MANAGER MENU?

16. Press the 'YES' button

Saving NVM data

17. The display will show the above and then return to the normal unset screen as shown in Step 1